

## ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr. 75964-0000, TX Nacogdoches Phone: 936-569-7941 Fax: 936-560-4685



**Special Features** 

## **3BR1224N125 3PH 125A Mod-Line 12/24 Cir. Al Bus Nema 1** *Eaton Corp*

| 20000                        |   |
|------------------------------|---|
| Catalog Number               | 3BR1224N125   |
| Manufacturer                 | Eaton Corp  |
| Description                  | Eaton BR Convertible Loadcenter, No Feed-Thru Lugs, Includes<br>BREQS125 Hold-Down Screw, Convertible Main, 125 A, C1,<br>Aluminum, Cover Included, NEMA1, Metallic, 10 Kaic, BR,<br>Combination, 24 Circuits, 12 Spaces, Four-Wire, Three-Phase, 208<br>Y/120, 240 V   |
| Weight per unit              | 21.0 (lbs/each)   |
| Product Category             | 20110214161650  |
| Features                     |   |
| amperage rating              | 125   |
| Cover Type                   | Cover included  |
| interrupt rating             | 10  |
| number of spaces             |   |
| Phase                        | 3   |
| Voltage Rating               | 208Y/120, 240V  |
| <b>Dimensions and Weight</b> |   |
| Depth                        | 3.88  |
| Height                       | 21  |
| Size                         | C1  |
| Width                        | 14.31   |
| Descriptions                 |   |
| Description                  | 3PH 125A MOD-LINE 12/24 CIR. AL BUS NEMA 1  |
| extra long description       | ETN 3BR1224N125 3 Ph/BR LC 125A Con   |
| Features                     | Specially designed for easy installation, Eaton's BR 1-inch load centers house the branch circuit breakers and the wiring required to distribute power to individual circuits. They serve as main breaker for service entrances or as main lug when adding circuits to existing service. The main breaker protects the entire panel and can be used as a service disconnect. The branch breakers protect the wires leading to individual electrical loads such as fixtures and outlets. |
| Long Description             | Eaton BR convertible loadcenter, No feed-thru lugs, includes BREQS125 hold-down screw, Convertible main, 125 A,C1, Aluminum, Cover included, NEMA1, Metallic, 10 kAIC, BR, Combination, 24 Circuits, 12 Spaces, Four-wire, Three-phase, 208 Y/120, 240 V  |
| Product Type                 | 3 PH/BR LC 125A Conv 12/24 CKT AI Bus   |
| Charles Factures             | No food thru lugo includes PDEOC135 hold down serow   |

No feed-thru lugs, includes BREQS125 hold-down screw



Mounting

standard

## ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr. 75964-0000, TX Nacogdoches Phone: 936-569-7941 Fax: 936-560-4685

Vessels and Equipment - Marine Vessels and Equipment - Other

Combination Mount

| Manufacturer Information                    |  |
|---|--|
| Brand                                       | EATON CUTLER-HAMMER  |
| GTIN  | 00786676443159   |
| Manufacturers Part Number                   | 3BR1224N125  |
| UPC   | 786676443159   |
| Taxonomies, Classifications, and Categorian | gories   |
| Category Description                        | LOADCENTERS & COVERS                                       |
| Туре  | Convertible loadcenter                                     |
| Packaging                                   |  |
| Carton                                      | 1  |
| Weight Per each                             | 21   |
| Uses, Certifications, and Standards         |  |
| Application                                 | OtherGeneration - Renewable Energy - Alternative           |
|   | EnergyGeneration - Conventional Energy - Conventional      |
|   | EnergyDatacenters - IT Space: CI and Hyper ConvergedMarine |

UL 67,UL 50