MILBANK ENERGYAT WORK

U3832



Catalog Number	U3832
Marketing Product Description	30 Ampere Fused Alternating Current Disc Pull Out
UPC	784572586925
Length (IN)	2.85
Width (IN)	5.2
Height (IN)	6
Weight (LB)	2.84
Brand Name	Milbank
Туре	Air Conditioner Disconnect
Special Features	3 Horse Power
Application	Metering Accessory
Standard	UL Listed;Type 3R
Voltage Rating	Up to 240 Volts Alternating Current
Amperage Rating	30 Ampere
Interrupt Rating	10,000 Ampere Interrupting Capacity
Number Of Poles	2
Тгір Туре	Thermal Overload and Short Circuit Current
Contact Configuration	Pull Out
Contact Rating	30 Ampere Up to 240 Volts Alternating Current
Connection	Pullout

Enclosure	Painted Steel
Mounting	Surface Mount
Size	2.85L x 5.2W x 6H
Conduit Connection	Knockouts

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

MILBANK ENERGYAT WORK

U3832



Catalog Number	U3832
Marketing Product Description	30 Ampere Fused Alternating Current Disc Pull Out
UPC	784572586925
Length (IN)	2.85
Width (IN)	5.2
Height (IN)	6
Weight (LB)	2.84
Brand Name	Milbank
Туре	Air Conditioner Disconnect
Special Features	3 Horse Power
Application	Metering Accessory
Standard	UL Listed;Type 3R
Voltage Rating	Up to 240 Volts Alternating Current
Amperage Rating	30 Ampere
Interrupt Rating	10,000 Ampere Interrupting Capacity
Number Of Poles	2
Trip Type	Thermal Overload and Short Circuit Current
Contact Configuration	Pull Out
Contact Rating	30 Ampere Up to 240 Volts Alternating Current
Connection	Pullout

Enclosure	Painted Steel
Mounting	Surface Mount
Size	2.85L x 5.2W x 6H
Conduit Connection	Knockouts

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.